

Poly Edge E 350 Phone guide

Table of contents

[Your Desktop Device](#)

[Use Your Desktop Device](#)

Your Desktop Device



Voicemail Indicator

The indicator is on the upper right corner of the phone. The light flashes red to indicate new messages.

Softkeys

The functions for the soft-key buttons appear directly above them on display. Their functions are context-sensitive, which means the function of the soft-keys changes depending on your current activity. For example, if you are conferencing, the soft-keys display functions related to the conference feature.

Home Button

The Home button is located to the right of the navigational keys. Press this button from any screen to return to the Home screen.

Navigation Button

By pressing left or right, you can scroll through the options and lists on the display up or down. To select an item, press the **OK** button in the center of the four-way navigation arrows.

Headset, Speaker, and Mute Keys

These keys are located along the right edge of the phone and used as they are stated.

Volume Key

The volume key is located at the bottom of the phone below the dial pad. This key adjusts the volume of the handset, headset, speaker, and phone's ringer.

Transfer Button

This button will transfer active calls to another number.

Message Button

This button gives you access to your voicemail messages.

Hold Button

This button will place a call on hold.

Back Button

This button cancels actions or returns to the previous screen when pressed.

Line Keys

These buttons indicate the status of your lines and associated activity. The backlighting informs you when a line is idle, ringing, in use, on hold, or disconnected.

Use Your Desktop Device

Place a Call

First, dial the number. Then, pick up the handset. For hands-free speakerphone – dial number, then press the **Speaker** button or press **Dial** softkey.

Answer a Call

Pick up the handset. For a hands-free speakerphone, press the **Answer** soft key or press the **Speaker** button.

Dial a Number From Your Directories

Press the **Home** button, and then select **Directories**. Proceed to **Contact Directory**. Select the contact, then the number from the Contact Information Screen, and then press **Ok**.

Dial a Number From Your Recent Calls

Press the **Home** button, then select **Directories**. Proceed to **Recent Calls**. Press the **Sort** softkey to sort and order calls; Press **Type** to display only specific calls. Select a call record to call the person.

Hold and Resume

From Lines, Calls, or Active Call view, press the **Hold** softkey or function button. To retrieve the call, press the **More** softkey and press the **Resume** softkey or **Hold** function button again.

Call Park / Call Retrieve

Call Park places a call on hold so that other users assigned to Call Park service can retrieve that call from any phone in the office.

To Park: Press the **Park** softkey (the Park softkey does the same thing as Hold and *68). Enter the extension where the call will be parked, and then press **#**.

To Retrieve: Press the **Retrieve** softkey. Enter the extension where the call was parked then **#**.

Transfer a Call

Announced Transfer: Press the **Transfer** button to place an active call on hold. Dial the number where you want to transfer the call. Once the third-party answers, announce the call and press the **Transfer** button.

Blind Transfer: Press the **Transfer** button to place an active call on hold. Press the **Blind** softkey (If you don't see Blind, press the **More** softkey,) Dial the number where you want to transfer the call.

Transfer to Voicemail: Press the **Transfer** button to place an active call on hold. Next, enter ***55** and dial the party's extension, then **#**.

Mute

Press the **Mute** function button to silence your phone's mouthpiece and speaker. To turn mute off, press **Mute** again.

Voicemail

Press **Messages** from home view or press the **Messages** function button. Then press the **Connect** softkey. Your phone will ring your voice portal. Enter your passcode, then **#**. Follow the voice prompts to listen to delete/save messages.

Call Forward

Press the **Forward** softkey from the home or lines view. Select the forwarding type and enter the number to forward your calls to. Then press **Enable** softkey. Calls Forwarded will be displayed on the LCD screen. To turn off Call Forwarding, press the **More** softkey and then press the **Forward** softkey. Select the forwarding type and press **Disable** softkey.

Bluetooth

You can pair your Poly Edge phone with a mobile device or headset and use it to place, answer, and manage calls.

To pair your headset to your Poly Edge E350 phone:

1. On the phone, press the **Home** button.
2. Select **Bluetooth**.
3. Select **Manage Devices**.
4. Select **Scan**.

The phone will search for available BlueTooth devices within range to pair with them. Locate and select the name of the headset to pair with it.

To reconnect a headset that was already paired:

1. Go to **Menu** and select **Bluetooth**.
2. Select **Manage Devices**.
3. Choose your device name from the list of paired devices and press **Connect**.

WiFi

To configure a voice VLAN, you must provision the following items on your DHCP server:

You must enable Wi-Fi before connecting to a Wi-Fi network.

Do one of the following:

1. Go to **Menu > Wi-Fi**.
2. Go to **Menu > Settings > Basic > Wi-Fi Menu**.

Note: Your system administrator determines the availability of these options.

3. Press the **Select** key to enable Wi-Fi, and then press **Save**.
4. Press **Reboot**.

After the phone reboots, it can connect to a wireless network.

Connect to a Wireless Network

After you enable Wi-Fi on your phone, connect to a wireless network.

Do one of the following:

1. Press the **Scan** softkey to scan for available networks and select one to enter information as required by the network's security settings.

Note: For a WPA2-Enterprise network, select the correct authentication mode.

2. Press the **Other** softkey to manually enter network settings, including SSID, security type, and password.
3. Select **Connect**.

Update Wireless Network Settings

You can update settings for a saved wireless network.

Do one of the following:

1. To change settings related to the current network, to re-attempt connection, or to forget/disconnect the network, select **Saved Network**.
2. To edit advanced network settings including IP settings, SSID, security options, and radio regulatory country domain, select **Advanced**.

Disconnect from a Wireless Network

To change wireless connections or switch to an Ethernet connection, disconnect from the current wireless network:

1. Select **Wi-Fi Menu**.
2. Select the connected wireless network SSID from the list.
3. Select **Disconnect**.

Remove a Saved Wireless Network

To remove any saved wireless network that is no longer necessary:

1. Select the connected wireless network SSID from the list.
2. Select **Forget**.

Visual Call Park

Visual Call Park is an optional Unified Communications functionality. Once requested, the appearance of the available Visual Call Parks is represented in the line keys / Busy Lamp Field (BLFs) on every phone that's in the customer's location. It is either vacant or occupied (with a parked call).

Everyone on the site sees the same parking spots and their status (whether a call is parked or not), and can either park a call in a vacant spot, or retrieve a call from an occupied spot.

For consistency, all phones in the location must be provisioned precisely the same way, in this case being the Poly Edge 350. The client must also select between 4 parking spots (up to 12 phones per site), or three parking spots (up to 16 phones per location).

To use Visual Call Park, while on an active call:

1. Press the **Home** button, so the Line Key view is displayed. Here you will see your available Visual Call Park spots.
2. Proceed to park the call at any vacant call park spot by tapping the **VISUAL CALL PARK** (VCP 1) spot.
3. Once this is complete, the call will be parked and indicated by a white phone icon.
4. Once the call is parked, everyone in the location can see the parked call occupying the parking spot.
5. Any user can then retrieve the call to his / her line freeing up that spot.
6. To retrieve the Parked Call, press the corresponding line key.